

# MX410



# ROLLS

4 CHANNEL FIELD/ENG MIXER

## FEATURES

- Four balanced XLR Inputs
- Two transformer-balanced XLR Outputs
- Switchable Output Level (Line level, or Mic level)
- 1/8" TRS Stereo Auxiliary Input
- Switchable Phantom Power for each input
- Dual 9V easy access Battery compartment
- Level controls for each channel
- 1/8" (3.5mm) Headphone Output - Level control
- 18 hour battery life
- Rolls PS27s external power supply included

# ROLLS

# 4 CHANNEL

# ENG/

# FIELD MIXER

BALANCED XLR INPUTS  
BALANCED XLR OUTPUTS  
HEADPHONE OUT  
3.5mm CAMERA OUTPUT

# ROLLS

5968 SOUTH 350 WEST S.L.C., UT 84107

PHONE: 801-263-9053

FAX: 801-236-9068



The Rolls MX410 is a compact four channel, ENG/Field Mixer, designed for the mobile audio/visual professional. Designed for remote operation and rough handling, the MX410 features a rugged, powder coated steel chassis with locking XLR mic inputs, each with switchable 18v phantom power, and L/C/R pan control. The front panel features easy access volume controls, an 1/8" stereo headphone jack with level control, and left and right output meters. The MX410 can operate for up to 18 hours on two 9 volt batteries or the Rolls PS27s AC adapter (included).

## SPECIFICATIONS

Input Impedance:	Mic:	600 Ohms XLR balanced
Output Attenuator:		-30 dB
Self Noise:		-65 dB maximum -90 dB typical
Max Gain:		+55 dB
S/N Ratio:		115 dB
THD:		.05%
Frequency Response:		20 Hz - 20 kHz   +0, -3 dB
Low Cut:		100 Hz
Max Input:		-20 dBV
Current Draw:		30 mA with no Phantom Power or Signal.
Phantom Power:		+18 VDC
Typical Battery Life:		18 Hrs. (2 mics, phan on, with headphone)
Connectors:		4 ea. Female XLR, 2 ea. Male XLR, 3 ea. 1/8" (3.5mm), 1 Center Negative power jack.
Power Adapter:		12VDC / 200 mA
Size:		9" W x 6.75" D x 1.5" H
Weight:		2.45 lbs

# MSRP: \$350 USD



Power Supply Included



6 75889 04100 2

# MADE IN USA

